

EMX512SC, EMX312SC, EMX212S

Powered Mixers



EMX512SC

SPX DIGITAL WITH EFFECT PROCESSOR YSProcessing 7U



EMX312SC

SPX DIGITAL WITH EFFECT PROCESSOR YSProcessing 7U



EMX212S

SPX DIGITAL WITH EFFECT PROCESSOR YSProcessing 7U

Rear Panel



High-performance mixer, power amplifier, graphic EQ, and digital effects integrated into compact, portable units.

- 12 versatile inputs: 1 through 4 for mono microphone or line, 5/6 and 7/8 for mono microphone/line or stereo line input, and 9/10 and 11/12 for stereo line input.
- Advanced Yamaha one-knob compressor on mono EMX512SC and EMX312SC input channels.
- Yamaha FCL system makes locating and eliminating feedback easier than ever.
- 16 digital SPX effect programs with adjustable parameters.
- Footswitch connector for effect on/off control.
- Standby switch can be used to mute performer's inputs while the stereo inputs remain active for background music playback.
- High-quality, high power output with remarkably efficiency and low heat generation.
- Connectors for external power amplifiers and effect processors.
- Independent 7-band graphic equalizers for the stereo and monitor outputs.
- Yamaha Speaker Processing.
- Forced air keeps the system cool.
- Optional rack mount hardware.

OPTIONS

RK512
Rack Mount Kit

FC5
Foot Switch



EMX512SC, EMX312SC, EMX212S

GENERAL SPECIFICATIONS

Model		EMX512SC	EMX312SC	EMX212S
Maximum output power	4	500W+500W	300W+300W	220W+220W
1kHz, THD+N 0.5%	8 / AC120V model	350W+350W	190W+190W	130W+130W
	8 / AC220-240V model	320W+320W	180W+180W	130W+130W
Total harmonic distortion		Less than 0.5%, +14dBu@ 20Hz-20kHz		
Frequency response		0, -3, +1dB, 20Hz-20kHz, 0dB@1kHz		
Equivalent input noise	20Hz-20kHz	-115dBu		
Crosstalk @1kHz		-65dB		
Phantom voltage		+15V, CH1-4:INPUT B, CH5/6-11/12:MIC		
CH&ST CH equalizer	HIGH	10kHz (Shelving)		
	MID	2.5kHz (Peaking)		
	LOW	100Hz (Shelving)		
Effect		16 program, Parameter control FOOT SW (ON/OFF)		
Level meter		2x5 point LED level meter [MAIN(L,R)]		
		5 point LED level meter [MONITOR]		
FCL Sensitivity		Input signal level \geq -75dBu: LED on CH1-4 MIC/LINE: MIC B Input, CH5/6-11/12 MIC Input		
Protection	Power Amplifier	POWER switch on/off mute DC-fault Thermal / heatsink temp \geq 90degrees celsius VI limiter / RL " 2 Clip limiter / THD \geq 1%, Indicator x 2		
	Power supply	Thermal / heatsink temp \geq 100degrees celsius		
Power consumption		550W	450W	350W
Dimensions (W x H x D)		442.5 x 284 x 264mm (17.4" x 11.2" x 10.4")		
Weight		8.0kg (17.6lbs)		

INPUT CHARACTERISTICS

Input Terminal	MIC/LINE	Actual Load Impedance	For Use With Nominal	Input Level			Connector	
				Sensitivity	Nominal	Max. Before Clip		
CH INPUT 1-4	XLR	MIC	2k	50-600 Mics	-60dBu	-35dBu	-15dBu	XLR3-31 type
					-30dBu	-5dBu	+15dBu	
	Phone	MIC	6k	600 Lines	-50dBu	-25dBu	-5dBu	TRS phone jack
					-20dBu	+5dBu	+25dBu	
CH INPUT 5/6,7/8	XLR	-	2k	50-600 Mics	-60dBu	-35dBu	-15dBu	XLR3-31 type
					-20dBu	+5dBu	+25dBu	
CH INPUT 9/10,11/12	Phone	-	10k	600 Lines	-20dBu	+5dBu	+25dBu	Phone jack
					-20dBu	+5dBu	+25dBu	
CH INPUT 9/10,11/12	XLR	-	2k	50-600 Mics	-60dBu	-35dBu	-15dBu	XLR3-31 type
					-20dBu	+5dBu	+25dBu	
CH INPUT 9/10,11/12	Pin	-	10k	600 Lines	-20dBu	+5dBu	+25dBu	RCA pin jack
					-20dBu	+5dBu	+25dBu	

OUTPUT CHARACTERISTICS

Output Terminal	Actual Source Impedance	For Use With Nominal	Output Level			Connector
			Model	Nominal	Max. before Clip	
SPEAKERS [A1,A2,B1,B2]	0.1	4 Speakers	EMX512SC	125W	500W	[A1,B1]SPEAKON [A2,B2]Phone jack
			EMX312SC	75W	300W	
			EMX212S	50W	200W	
MAIN OUT[L,R]	600	10k Lines	-	+4dBu	+20dBu	Phone jack
EFFECT OUT	600	10k Lines	-	+4dBu	+20dBu	Phone jack
MONITOR OUT	600	10k Lines	-	+4dBu	+20dBu	Phone jack
REC OUT[L,R]	600	10k Lines	-	-10dBu	+10dBu	RCA pin jack

DIMENSIONS

unit : mm

