

2 CH POWERED MIXER



FEATURES

- **6 MONO INPUT 2 CHANNEL POWERED MIXER**
This powered mixer has maximum output of 150W +150W(300W with bridged mono). Any sound source of microphones, cassette desk, compact disc and electronic instruments can be applied to mono input channel.
- **EACH INPUT CHANNEL WITH 3 BAND EQUALIZER**
3 Band equalizers are provided to adjust the acoustic characteristics according to microphone, speaker and room structure.
- **MODE SELECT**
The input signals for the two channels can be selected as MAIN+MAIN, MAIN+MONITOR, or MAIN(bridged mono).
- **TAPE IN, AUX IN**
There are used for play back of tape desk, and other electronic instruments, such as an electronic keyboard.
- **7 BAND EQUALIZER**
It can shape the response of the sound system to suit almost any location.
- **BUILT IN DSP**
Built in 3 kind of digital effect(small hall, large hall, vocal).
- **+48V PHANTOM POWER**
Phantom power is provided at each mono channel for condenser microphones.

SPECIFICATIONS

- **ELECTRICAL** *0dB=0.775Vrms
 - . Rated Output
 - Power Amp 150W/+150W, 4Ω
 - Main/Monitor +4dB/600Ω, UNBAL
 - . Input Sensitivity/Impedance
 - Lo-z/Hi-z -50dB/40dB, 600Ω, BAL
 - Tape In -10dBV/10KΩ, UNBAL
 - AUX In -10dB/10KΩ, UNBAL
 - . Frequency Response(+1/-2dB) 20Hz~30KHz
 - . T.H.D(20Hz~20KHz) Mixer Section 0.1%
 - Amp Section 0.5%
 - . Tone Control(High, Mid, Low)
 - High, Low(12KHz, 80Hz) ±15dB
 - Mid(2.5KHz) ±12dB
 - . Graphic Equalizer (±12dB Maximum)
 -7 Band(63Hz, 160Hz, 400Hz, 1K, 2.5K, 6.4K, 12K)
 - . EIN -128dB
 - . Buss Noise -78dB
 - . Crosstalk -70dB
- **GENERAL**
 - . Power Source AC 110V-240V, 50/60Hz
 - . Power Consumption 270W
 - . Weight 15kg
 - . Dimensions 465(W) × 272(H) × 285(D)mm

