

interM L800/1400/1800/2400

Professional Power Amplifier



- 2ohm-load stable per channel, 4 ohm-load stable in bridge mono
- 2U rack space
- Selectable High Pass Filter on each channel
- Clip limiter circuitry
- Forced air cooled (front panel intake, rear panel exhaust)
- Front panel indicators for different operating modes
- Front panel indicators for output signal level, clip, protect, and power
- Rack Ears for permanent installation in a standard 19" (rack mount width) enclosure.
- Detachable AC power cord

Specifications

		L800	L1400	L1800	L2400
Power Output Level	8ohm stereo	200W	280W	360W	500W
	4ohm stereo	300W	450W	600W	750W
	2ohm stereo	430W	700W	900W	1200W
	8ohm bridged	600W	900W	1200W	1500W
	4ohm bridged	800W	1400W	1800W	2400W
Input Sensitivity / Impedance		≥20kohm(Balance/unBalance)			
Frequency Response (0.5dB)		20Hz~20kHz : ±0/1dB, -3dB : 5Hz~70kHz			
T.H.D. (f=20Hz~20kHz, Half Power)	8/4ohm stereo	Less than 0.03%			
	8ohm bridged	Less than 0.03%			
Damping Facto		More than 400			
Power Source		AC 100V/120V/230V/240V, 50/60Hz			
Power Consumption		3A	3.5A	4A	4.5A
		660W	770W	880W	990W
Weight		14kg	14.4kg	15kg	15.64kg
Dimensions		482(W)x 88(H) x 369(D) mm			